

## 9501-DCDA-3G • Down-Converter/DA with 3G/HD/SD-SDI Input, Reclocking, SD-SDI and Analog Video/Audio Outputs



The **9501-DCDA-3G** provides 3G/HD-to-SD down-conversion with ARC and has versatility in providing up to four SD-SDI and/or analog composite outputs as well as up to four reclocked SDI input copies. The space-saving design of the 9501-DCDA-3G provides for high density, allowing two cards to be collocated in adjacent slots and served by a single, standard width "split" rear module. Up to 20 of the 9501-DCDA cards can be installed in a 20-slot frame.

The card can pass SD signals with re-aspect, if needed. AFD processing can detect an incoming AFD code and correspondingly set scaling to track with AFD. This processor also allows independent custom ARC to be applied for each incoming AFD code, and set the desired AFD code to be inserted on the output, even if there is no code detected on the input. Analog audio outputs can be de-embedded from selected embedded audio channels. The 9501-DCDA can rate-convert 23.98 frame video to 59.94 fields, move progressive to interlace and is equipped with extensive user programmable reticule overlays. Two discrete character burn strings can be inserted on output video, with each string inserted as static text and/or insert only upon LOS.

The data path is 10-bit with 12-bit analog encoding. Full proc control allows adjustment of luma gain, luma lift, color gain, and color phase. Preset save/load allows saving custom card settings while allowing one-button revert to factory settings.

Preset save/load allows saving custom card settings while allowing one-button revert to factory settings. Layered presets allow invoking changes related only to a specific area of concern (audio routing, for example) while not changing any other processing settings or aspects. Full user DashBoard™ or Remote Control Panel remote control allows full status and control access over a standard Ethernet network.

### Alternate Base Model

• **9501-DCDA-HD** Down-Converter/DA with HD/SD-SDI Input, Reclocking, SD-SDI and Analog Video/Audio Outputs

### FEATURES



Low power/high-density design allows up to 20 cards per frame; less than 18 Watts per card	User DashBoard output selection flexibly allows SDI or CVBS outputs on four processed-output BNCs
Supports all popular formats: 480i, 576i, 720p, 1080i, 1080pSF, 1080p	Dual independent text/character burn-in insertion allows condition-based insertion (such as basic ID text for valid input and different text message for failover/LOS conditions)
Built-in x4 DAs for both reclocked and processed outputs	Full timecode and CEA 708 / CEA 608 conversion to SD VITC timecode and closed-captioning. Option <b>+LTC</b> allows bidirectional transfer between embedded video timecode formats and audio LTC.
Dual SDI inputs with manual GUI select and basic failover function	Remote control/monitoring via Dashboard™ software or OGCP-9000 remote control panels
Economical solution for 3G/HD down-conversion to legacy SD monitoring systems. HD version further economizes for environments requiring only HD/SD support (field upgradeable to 3G with software license upload if later desired).	Hot-swappable
Auto-format detect/ down-conversion of SMPTE 424M/292/259M formats	Five year warranty
Down-conversion scaling includes user-configurable ARC and AFD-controlled ARC	
Full embedded audio control with selectable downmix and analog audio de-embed	
Color framing preserved on CVBS outputs for all conversions	

### OPTIONS


3G Software Option Upgrade ( <b>+3G</b> ) – Upgrades 9501-DCDA-HD card to 9501-DCDA-3G functionality/specifications.
Color Correction ( <b>+COLOR</b> ) – Provides independent RGB channel controls for luma, black, and gamma. Ultra-fast response time. The color correction feature is perfectly suited for use with Cobalt OGCP-9000/CC Remote Control Panel.
Frame Sync Software Option ( <b>+FS</b> ) – Adds frame sync to 9501-DCDA-3G card. Provides full vertical and horizontal offset and frame delay controls. Glitch-free handling of embedded audio when a frame is dropped or duplicated.
Audio LTC Software Option ( <b>+LTC</b> ) – Offers bidirectional transfer and conversion between video timecode formats and audio LTC. Audio LTC can be received or sent over various card audio channels.
Extended Frame Sync Delay Option ( <b>+DLY</b> ) – Increases frame buffer to provide adjustable audio/video delay buffer capacity to over 9 seconds for SD video, 1.5 seconds for HD video, or 0.8 seconds for 3G video. (Add-on to option +FS; option +FS required)




# 9501-DCDA-3G • Down-Converter/DA with 3G/HD/SD-SDI Input, Reclocking, SD-SDI and Analog Video/Audio Outputs



RM20-9501-A




RM20-9501-A/S




Note: Although this rear module offers only two SDI/compst OUT BNCs, the two outputs on the rear module correlate to card output channels 3 and 4.

RM20-9501-B



RM20-9501-C/S-DIN  
RM20-9501-C/S-HDBNC



RM20-9501-F-DIN  
RM20-9501-F-HDBNC

# 9501-DCDA-3G • Down-Converter/DA with 3G/HD/SD-SDI Input, Reclocking, SD-SDI and Analog Video/Audio Outputs

## SPECIFICATIONS

Note: Inputs/outputs are a function in some cases of rear I/O module used.

### Power

< 18 Watts

### SDI Input

Number of Inputs: (2) 3G/HD/SD-SDI BNCs. GUI-selectable.  
Standards: SMPTE 259M, 292M, 424M (9501-DCDA-3G only)  
Supported Formats: 1080p59.94, 50, 29.97, 24, 23.98, 1080i59.94, 50, 720p59.94, 50, 29.97, 24, 23.98, 625i, 525i  
Cable Length, Minimum, 3G/HD/SD (Belden 1694A): 120m / 180m / 360m  
Return Loss: 15 dB up to 1.485 GHz, 10 dB up to 2.970 GHz

### Video Outputs

Number of Outputs: (4) dedicated reclocked output BNCs. Up to 4 processed SD-SDI (or CVBS output) BNCs. GUI-selectable.  
SDI Signal Level: 800 mV nominal  
SDI Return Loss: >15 dB up to 1.485 GHz, >10 dB up to 2.970 GHz  
SDI Jitter: SD: < 0.2 UI  
SDI Embedded Audio: 16-Ch

### Frame Sync Audio/Video Delay (option +FS)

Max offset: 20 frames  
Latency (min): 1 frame  
Option +DLY Delay (3G/HD/SD): >800 msec / >1580 msec / >9000 msec

### Reference Video Input

Number of Inputs: (2) looping (openGear® frame)  
Standard: Tri-level sync (SMPTE 274) and black burst (NTSC and PAL)

### Analog Audio Output

Number of Outputs: 4-Ch (max) balanced using 3-wire Phoenix connectors  
Maximum Output Level: +24 dBu @ 0 dBFS  
DAC Resolution: 24-bit

## ORDERING INFORMATION

**9501-DCDA-3G** Down-Converter/DA with 3G/HD/SD-SDI Input, Reclocking, SD-SDI and Analog Video/Audio Outputs

**9501-DCDA-HD** Down-Converter/DA with HD/SD-SDI Input, Reclocking, SD-SDI and Analog Video/Audio Outputs

**RM20-9501-A** 20-Slot Frame Rear I/O Module (Standard Width) (2) 3G/HD/SD-SDI Input BNCs, (4) 3G/HD/SD-SDI Reclocked Output BNCs, (4) Output BNCs (GUI-selectable as SD-SDI and/or Analog CVBS)

**RM20-9501-A/S** 20-Slot Frame Rear I/O Module (Split; supports 2 cards) 3G/HD/SD-SDI Input BNC, (2) HD/SD-SDI Reclocked Output BNCs, (2) Output BNCs (GUI-selectable as SD-SDI and/or Analog CVBS) (connections are per card)

**RM20-9501-B** 20-Slot Frame Rear I/O Module (Standard Width) (2) 3G/HD/SD-SDI Input BNCs, (2) 3G/HD/SD-SDI Reclocked Output BNCs, (2) Output BNCs (GUI-selectable as SD-SDI and/or Analog CVBS), (4) Analog Audio Outputs

**RM20-9501-C/S-DIN** 20-Slot Frame Rear I/O Module (Split; supports 2 cards) (2) 3G/HD/SD-SDI Input BNCs, (4) HD/SD-SDI Reclocked Outputs, (4) Outputs (GUI-selectable as SD-SDI and/or Analog CVBS) (connections are per card; all connectors DIN1.0/2.3)

**RM20-9501-C/S-HDBNC** 20-Slot Frame Rear I/O Module (Split; supports 2 cards) (2) 3G/HD/SD-SDI Input BNCs, (4) HD/SD-SDI Reclocked Outputs, (4) Outputs (GUI-selectable as SD-SDI and/or Analog CVBS) (connections are per card; all connectors HD-BNC)

**RM20-9501-F-DIN** 20-Slot Frame Rear I/O Module (Standard Width, Hi-Density) (2) 3G/HD/SD-SDI Inputs, (4) 3G/HD/SD-SDI Reclocked Outputs, (4) Outputs (GUI-selectable as SD-SDI and/or Analog CVBS), (4) Analog Audio Outputs (all coaxial connectors DIN1.0/2)

**RM20-9501-F-HDBNC** 20-Slot Frame Rear I/O Module (Standard Width, Hi-Density) (2) 3G/HD/SD-SDI Inputs, (4) 3G/HD/SD-SDI Reclocked Outputs, (4) Outputs (GUI-selectable as SD-SDI and/or Analog CVBS), (4) Analog Audio Outputs (all coaxial connectors HD-BNC)

**+3G** Software license upgrade for 9501-DCDA-HD card. Upgrades card to 9501-DCDA-3G functionality/specifications.

**+COLOR** Color Correction Software Option

**+FS** Frame Sync Software Option

**+DLY** Extended Frame Sync Delay Option (add-on to option +FS; option +FS required)

**+LTC** Audio LTC Option